



N-Channel MOSFET

2SK3018-HF

■ Features

- V_{DS} (V) = 30V
- I_D = 0.1 A
- $R_{DS(ON)} < 8 \Omega$ ($V_{GS} = 4V$)
- $R_{DS(ON)} < 13 \Omega$ ($V_{GS} = 2.5V$)
- Pb-Free Package May be Available.

The G-Suffix Denotes a Pb-Free Lead Finish

■ Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

Parameter	Symbol	Rating	Unit
Drain-Source Voltage	V_{DS}	30	V
Gate-Source Voltage	V_{GS}	± 20	
Continuous Drain Current	I_D	100	mA
Pulsed Drain Current (Note.1)	I_{DM}	400	
Power Dissipation	P_D	200	mW
Junction Temperature	T_J	150	$^\circ\text{C}$
Storage Temperature Range	T_{stg}	-55 to 150	

Note.1: PW $\leqslant 10\mu\text{s}$, Duty Cycle $\leqslant 1\%$

■ Electrical Characteristics $T_a = 25^\circ\text{C}$

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Drain-Source Breakdown Voltage	V_{DSS}	$I_D=250 \mu\text{A}$, $V_{GS}=0\text{V}$	30			V
Zero Gate Voltage Drain Current	I_{DSS}	$V_{DS}=30\text{V}$, $V_{GS}=0\text{V}$			1	μA
Gate-Body Leakage Current	I_{GSS}	$V_{DS}=0\text{V}$, $V_{GS}=\pm 20\text{V}$			± 1	μA
Gate Threshold Voltage	$V_{GS(th)}$	$V_{DS}=3\text{V}$, $I_D=0.1\text{mA}$	0.8		1.5	V
Static Drain-Source On-Resistance	$R_{DS(on)}$	$V_{GS}=4\text{V}$, $I_D=10\text{mA}$			8	Ω
		$V_{GS}=2.5\text{V}$, $I_D=1\text{mA}$			13	
Forward Transconductance	g_{FS}	$V_{DS}=3\text{V}$, $I_D=10\text{mA}$	20			mS
Input Capacitance	C_{iss}	$V_{GS}=0\text{V}$, $V_{DS}=5\text{V}$, $f=1\text{MHz}$		13		pF
Output Capacitance	C_{oss}			9		
Reverse Transfer Capacitance	C_{rss}			4		
Turn-On Delay Time	$t_{d(on)}$	$V_{GS}=5\text{V}$, $V_{DS}=5\text{V}$, $I_D=10\text{mA}$, $R_L=500\Omega$, $R_G=10\Omega$		15		ns
Turn-On Rise Time	t_r			35		
Turn-Off Delay Time	$t_{d(off)}$			80		
Turn-Off Fall Time	t_f			80		

■ Marking

Marking	KN F
---------	------

N-Channel MOSFET

2SK3018-HF

■ Typical Characteristics




Fig.1 Typical output characteristics




Fig.2 Typical transfer characteristics




Fig.3 Gate threshold voltage vs. channel temperature




Fig.4 Static drain-source on-state resistance vs. drain current (I)




Fig.5 Static drain-source on-state resistance vs. drain current (II)




Fig.6 Static drain-source on-state resistance vs. gate-source voltage




Fig.7 Static drain-source on-state resistance vs. channel temperature




Fig.8 Forward transfer admittance vs. drain current




Fig.9 Reverse drain current vs. source-drain voltage (I)


N-Channel MOSFET**2SK3018-HF****■ Typical Characteristics**

Fig.10 Reverse drain current vs. source-drain voltage (II)




Fig.11 Typical capacitance vs. drain-source voltage



Fig.12 Switching characteristics
(See Figures 13 and 14 for the measurement circuit and resultant waveforms)

Fig.13 Switching time measurement circuit




Fig.14 Switching time waveforms