

Himax AV TCON

<i>Part No.</i>	<i>Features</i>	<i>Resolution</i>	<i>PKG</i>	<i>Status</i>
HX8801	CVBS	280 x 220, 528 x 220, 480 x 234, 960 x 234(S), 1152 x 234(S), 1440 x 234(S)	48 LQFP	MP
HX8806	CVBS ; 8 zoom modes	Stripe : 1200, 1440 Good application in 7" Analog panel	48 LQFP	MP
HX8802B	Input : Serial RGB 8-bit Analog RGB	240 x 234, 320 x 240, 480 x 234, 640 x 240, 720 x 234, 960 x 234(S) 1200 x 234(S), 1440 x 234(S)	64 LQFP	MP
HX8802- C (HX8802A+PWM)	Input : Serial RGB 8-bit Output : Analog RGB 3ch PWM	280 x 220, 528 x 220, 1152 x 234(S) <u>320 x 240, 480 x 234, 960 x 234(S)</u> <u>1440 x 234(S)</u>	64 LQFP	MP
HX8817	Input : 601/656/RGB-T/RGB18 Output : Analog RGB 2ch PWM , 8 zoom modes	Delta : 480, 960 Stripe : 960, 1200, 1440	64 LQFP	MP
HX8819A	Input : RGB24 Output : RGB18 Dithering	800x480 : FB 640x480 : FC	64 TQFP	MP
HX8824- A	Input : 601/656/RGB24 Output : RGB24/RGB18 Scaler,OSD,BCHS,1DSharpness Programmable Gamma, Dithering 2ch PWM	640 x 480, 800 x 480, 852 x 480, 800 x 600,	100 LQFP	MP

光碁科技股份有限公司(台灣)
CERAMATE TECHNICAL CO., LTD.
 桃園縣蘆竹鄉南崁路二段 66-5 號 1 樓
1F, NO.66-5, SEC.2, NAN-KAN RD., LUCHU,
TAOYUAN, TAIWAN, R.O.C
TEL: 886-3-3214525 FAX: 886-3-3521052
 E-mail: brook@ceramate.com.tw

光碁科技深圳辦事處(深圳)
CERAMATE TECHNICAL CO., LTD. (SHEN ZHEN)
 深圳市上步南路國企大廈 B 棟(永輝樓) 24G 室
 ROOM 24G,(YONG HUI BUILDING) B DONG, GUO QI DA
 SHA, SHANGBU SOUTH RD., SHENZHEN, CHINA
 Tel: 86-755-61637041~43 Fax : 86-755-61637040
 E-mail: jun.dong@163.com

瑞基電子有限公司(蘇州)
SU ZHOU PRONICS ELECTRONICS CO., LTD.
 蘇州市新區濱河路 813 號
 NO.813, BINHE ROAD, SUZHOU NEW DISTRICT ,
 JIANGSU, CHINA
 TEL:86-512-68410323 FAX: 86-512-68410313
 E-mail: helen_niu@pub.sz.jsinfo.net