

SPECIFICATION SHEET

JFW MODEL 50PD-567

4 WAY REACTIVE POWER DIVIDER/COMBINER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	800-3000 MHz
Impedance	50 Ohms nominal
VSWR	1.5:1 maximum
Insertion Loss (above 6 dB split)	1.0 dB maximum
Amplitude Tracking	± 0.4 dB
Phase Tracking	± 5°
Isolation	20 dB minimum
Matched Input Power	5 Watts average @ 25°C 100 Watts peak (1 microsecond)
Operating Temperature Range	-40°C to +85°C
RF Connector	N, SMA, BNC or TNC female
Physical Size	See outline drawing 092-3869 (N)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	12/15/2005		BAC 12/15/2005				