

International **IR** Rectifier

FRED

PD - 20371D

HFA35HB120C

Ultrafast, Soft Recovery Diode

Features

- Reduced RFI and EMI
- Reduced Snubbing
- Extensive Characterization of Recovery Parameters
- Hermetic
- Ceramic Eyelets

$V_R = 1200V$

$I_{F(AV)} = 15A$

$Q_{rr} = 370\text{ns}$

Description


These Ultrafast, soft recovery diodes are optimized to reduce losses and EMI/RFI in high frequency power conditioning systems. An extensive characterization of the recovery behavior for different values of current, temperature and di/dt simplifies the calculations of losses in the operating conditions. The softness of the recovery eliminates the need for a snubber in most applications. These devices are ideally suited for power converters, motors drives and other applications where switching losses are significant portion of the total losses.

Absolute Maximum Ratings

	Parameter	Max.	Units
V_R	Cathode to Anode Voltage (Per Leg)	1200	V
$I_{F(AV)}$	Continuous Forward Current, $\textcircled{1} T_C = 100^\circ\text{C}$	15	A
I_{FSM}	Single Pulse Forward Current, $\textcircled{2} T_C = 25^\circ\text{C}$ (Per Leg)	80	
$P_D @ T_C = 25^\circ\text{C}$	Maximum Power Dissipation	63	W
T_J, T_{STG}	Operating Junction and Storage Temperature Range	-55 to +150	$^\circ\text{C}$

Note: $\textcircled{1}$ D.C. = 50% rect. wave

$\textcircled{2}$ 1/2 sine wave, 60 Hz , P.W. = 8.33 ms



HFA35HB120C

International
Rectifier

Electrical Characteristics (Per Leg) @ $T_J = 25^\circ\text{C}$ (unless otherwise specified)

	Parameter	Min.	Typ.	Max.	Units	Test Conditions
V_{BR}	Cathode Anode Breakdown Voltage	1200	—	—	V	$I_R = 250\mu\text{A}$
V_{FM} See Fig. 1	Max Forward Voltage	—	—	3.3	V	$I_F = 7.0\text{A}$
		—	—	4.4		$I_F = 15\text{A}$
		—	—	2.8		$I_F = 7.0\text{A}, T_J = 125^\circ\text{C}$
I_{RM} See Fig. 2	Max Reverse Leakage Current	—	—	10	μA	$V_R = V_R \text{ Rated}$
		—	—	1.0	mA	$V_R = V_R \text{ Rated}, T_J = 125^\circ\text{C}$
C_T	Junction Capacitance, See Fig. 3	—	10	15	pF	$V_R = 200\text{V}$
L_S	Series Inductance	—	8.7	—	nH	Measured from anode lead to cathode lead, 6mm (0.025 in) from package

Dynamic Recovery Characteristics (Per Leg) @ $T_J = 25^\circ\text{C}$ (unless otherwise specified)

	Parameter	Min.	Typ.	Max.	Units	Test Conditions
t_{rr1}	Reverse Recovery Time	—	58	100	ns	$T_J = 25^\circ\text{C}$ See Fig.
		—	110	165		$T_J = 125^\circ\text{C}$ 5
I_{RRM1}	Peak Recovery Current	—	5.4	8.1	A	$T_J = 25^\circ\text{C}$ See Fig.
		—	7.2	10.8		$T_J = 125^\circ\text{C}$ 6
Q_{rr1}	Reverse Recovery Charge	—	185	370	nC	$T_J = 25^\circ\text{C}$ See Fig.
		—	395	590		$T_J = 125^\circ\text{C}$ 7
$di_{(rec)M}/dt_1$	Peak Rate of Fall of Recovery Current During t_b	—	255	380	A/ μs	$T_J = 25^\circ\text{C}$ See Fig.
		—	160	240		$T_J = 125^\circ\text{C}$ 8

Thermal - Mechanical Characteristics

	Parameter	Typ.	Max.	Units
R_{thJC}	Junction-to-Case, Single Leg Conducting	—	2.0	°C/W
Wt	Weight	9.3	—	g




Fig. 1 - Maximum Forward Voltage Drop Vs.
Instantaneous Forward Current (Per Leg)




Fig. 2 - Typical Reverse Current Vs. Reverse
Voltage (Per Leg)




Fig. 3 - Typical Junction Capacitance Vs.
Reverse Voltage (Per Leg)




Fig. 4 - Maximum Thermal Impedance Z_{thJC} Characteristics (Per Leg)

HFA35HB120C




Fig. 5 - Typical Reverse Recovery vs. di_f/dt

International
IR Rectifier




Fig. 6 - Typical Recovery Current vs. di_f/dt




Fig. 7 - Typical Stored Charge vs. di_f/dt




Fig. 8 - Typical $di_{(rec)M}/dt$ vs. di_f/dt

International
IR Rectifier

HFA35HB120C




Fig. 9 - Reverse Recovery Parameter Test Circuit





Fig. 10 - Reverse Recovery Waveform and Definitions

Case Outline and Dimensions — TO-254AA



NOTES:

1. DIMENSIONING & TOLERANCING PER ASME Y14.5M-1994.
2. ALL DIMENSIONS ARE SHOWN IN MILLIMETERS [INCHES].
3. CONTROLLING DIMENSION: INCH.
4. CONFORMS TO JEDEC OUTLINE TO-254AA.

PIN ASSIGNMENTS

- 1 = ANODE 1
- 2 = COMMON CATHODE
- 3 = ANODE 2

International
IR Rectifier

IR WORLD HEADQUARTERS: 233 Kansas St., El Segundo, California 90245, USA Tel: (310) 252-7105
TAC Fax: (310) 252-7903

Visit us at www.irf.com for sales contact information.
Data and specifications subject to change without notice. 08/02