

# AAP200X ECM Microphone Pre-Amplifier

## PRELIMINARY DATA

#### **DESCRIPTION**

The AAP200C is part of AAI's new family of specialty products for Portable Electronics applications, in this case aimed at two terminal ECMs requiring integrated pre-amplifiers. The AAP200X ECM pre-amplifiers offer ultra low noise, require low current and feature ultra low input capacitance.

The AAP200X family will be offered in a chip scale SMD package. The package size is a tiny  $630\mu m\ x$   $530\mu m$ , and its height is  $350\mu m$  including solder bumps.

The AAP200X is offered in a chip scale SMD package with a size and aspect ratio (630μm x 530μm) that is optimum for the smallest (2mm dia.) microphones. The lead free solder pads are nominally 110μm dia. The AAP200X is supplied in tape and reel packaging.

The AAP200X family has multiple operating voltage and gain options available, where the 'X' suffix designates the gain value. The following options available are:


• AAP200A: Gain = 16dB  $V_{op} = 1.25V$ • AAP200B: Gain = 19dB  $V_{op} = 1.25V$ • AAP200C Gain = 16dB  $V_{op} = 1.33V$ • AAP200D Gain = 19dB  $V_{op} = 1.33V$ 




#### **FEATURES**

- Multiple gain options:
  - 16dB
  - 19dB
- Multiple output voltage options
  - 1.25V
  - 1.33V
- Low quiescent current, 200μA typical (VDD=1.8V, R<sub>L</sub>=2.2kΩ)
- Low noise performance
- Low input capacitance, 0.35uA typical
- < 0.5% THD typical for output swing = 250mV peak to peak.
- Small die size: 630µm x 530µm
- Suitable for small microphones down to 2mm diameter

## PIN CONFIGURATION: 4-Lead Micro SMD




TOP VIEW




BOTTOM VIEW

## **Functional Block Diagram**



# **Typical Test Conditions**



## **MAXIMUM RATINGS**

PARAMETER	SYMBOL	PARAMETERS		UNITS	CONDITIONS
		MIN.	MAX.		
Applied Voltage (all pins)		-0.5	2	V	Max voltage between pin and GND
Supply Voltage	VDD	ı	$(IDD_{MAX} * R_L) + V_{op}$	V	
Supply Current	IDD		2	mA	
ESD	V <sub>esd,out</sub>	2500		V	OUT terminal
	$V_{esd}$	2000		V	Other terminals
Operating Ambient Temp		-40	85	°C	
Storage Temp Range		-40	100	°C	
Performance Operating Temp Range		-5	55	°C	

## **ELECTRICAL CHARACTERISTICS**

Unless otherwise stated: T=25°C, VDD=1.8V,  $V_{in}$ =-44dBVrms,  $R_L$ =2.2k $\Omega$ , F=1kHz,  $C_{mic}$ =5pF

PARAMETER	SYMBOL	PARAMETERS		UNITS	CONDITIONS	
		MIN	TYP	MAX		
OPERATING SUPPLY						
Quiescent Output (option A & B)	V <sub>op</sub>	1.2	1.25	1.3	V	
Quiescent Output (option C & D)	V <sub>op</sub>	1.3	1.33	1.4	V	
Supply Current (option A & B)	IDD		250		μА	
Supply Current (option C & D)	IDD		200		μА	
PSRR			60		dB	
AC CHARACTERISTICS	-					
Transfer Function (option A & C)	TF	16	16.5	17	dB	Source impedance = 500Ω
Transfer Function (option B & D)	TF	18.5	19.5	20.5	dB	Source impedance = $500\Omega$
Gain Variation over Temp	Δ Αν			0.1	dB	-5°C < T < 55°C
Lower 3dB Frequency	f <sub>LOW</sub>		20		Hz	Cc = 82nF, TF = 17dB
Upper 3dB Frequency	f <sub>HIGH</sub>	20	100		kHz	TF = 16dB
Overload Margin, input	$V_{inmax}$			40	mVpp	1% distortion, TF=19dB
Overload Margin, output	V <sub>outmax</sub>	_		400	mVpp	1% distortion, TF=19dB
Input Referred Noise	e <sub>n</sub>		2.6		μV RMS	TF=19dB; C <sub>mic</sub> shorted, A-weighted values
Input Referred Noise	e <sub>n</sub>		3.0		μV RMS	TF=16dB; C <sub>mic</sub> shorted, A-weighted values

PARAMETER	SYMBOL	PARAMETERS			UNITS	CONDITIONS
		MIN	TYP	MAX		
Total Harmonic Distortion	THD		0.3		%	
Input Capacitance	C <sub>IN</sub>		0.3		pF	
Input Impedance	Z <sub>IN</sub>	10			GΩ	
Output Impedance	Z <sub>OUT</sub>			50	Ω	

#### PIN DESCRIPTION

PIN	NAME	DESCRIPTION
1	NC	Not connected
2	OUT	Output. Also used for 'phantom' power supply input.
3	GND	Ground
4	IN	Input

## **APPLICATION**

## VDD Supply Voltage

The AAP200x is designed to use the output pin as the power supply input. This is referred to as the 'phantom' power supply input to the OUT pin. A load resistor, R<sub>L</sub>, must be used in series with the VDD supply. Refer to the table below for recommended R<sub>L</sub> values that correspond to various supply voltage ranges.

PARAMETER	SYMBOL	VOLTAGE RANGE		VOLTAGE RANGE		UNITS	RECOMMENDED R <sub>L</sub>	NOTES
		MIN	TYP	MAX				
Power Supply	VDD	1.5	1.6	2	V	$R_L$ =250 $\Omega$	A & B versions only	
		1.8	2	5	V	$R_L$ =3.3k $\Omega$		
		1.6	1.8	3.6	V	$R_L=2.2k\Omega$	Applies to all version	
		3.5	5	10	V	$R_L=10k\Omega$		


## Light Sensitivity

If your particular application has the possibility of the AAP200x being exposed to direct or indirect light, we recommend the application of an opaque underfill to limit the devices exposure to light(on the solder bumped side). Light exposure to the device may or may not have negative effects on the device performance (varies per application).

## **ORDERING TABLE**


Ordering PN	Description	Package	<b>Packing Type</b>	<b>Packing Qty</b>
AAP200A S-M4A-G-LF-W	ECM Pre-Amp, 16dB Gain, $V_{op} = 1.25V$	4-Pin Micro SMD	Waffle Pack	TBD
AAP200A S-M4A-G-LF-TR	ECM Pre-Amp, 16dB Gain, $V_{op} = 1.25V$	4-Pin Micro SMD	T&R	3500
AAP200B S-M4A-G-LF-W	ECM Pre-Amp, 19dB Gain, $V_{op} = 1.25V$	4-Pin Micro SMD	Waffle Pack	TBD
AAP200B S-M4A-G-LF-TR	ECM Pre-Amp, 19dB Gain, $V_{op} = 1.25V$	4-Pin Micro SMD	T&R	3500
AAP200C S-M4A-G-LF-W	ECM Pre-Amp, 16dB Gain, $V_{op} = 1.33V$	4-Pin Micro SMD	Waffle Pack	TBD
AAP200C S-M4A-G-LF-TR	ECM Pre-Amp, 16dB Gain, $V_{op} = 1.33V$	4-Pin Micro SMD	T&R	3500
AAP200D S-M4A-G-LF-W	ECM Pre-Amp, 19dB Gain, $V_{op} = 1.33V$	4-Pin Micro SMD	Waffle Pack	TBD
AAP200D S-M4A-G-LF-TR	ECM Pre-Amp, 19dB Gain, $V_{op} = 1.33V$	4-Pin Micro SMD	T&R	3500

## **PACKAGE DIMENSIONS**



**Bottom View** 

## **TAPE AND REEL CONFIGURATION**



The following is a brief overview of certain terms and conditions of sale of product. For a full and complete copy of all the General Terms and Conditions of Sale, visit our webpage http://www.asicadvantage.com/terms.htm.

## **LIMITED WARRANTY**

The product is warranted that it will conform to the applicable specifications and be free of defects for one year. Buyer is responsible for selection of, use of and results obtained from use of the product. Buyer indemnifies and holds ASIC Advantage, Inc. harmless for claims arising out of the application of ASIC Advantage, Inc.'s products to Buyer's designs. Applications described herein or in any catalogs, advertisements or other documents are for illustrative purposes only.

### **CRITICAL APPLICATIONS**

Products are not authorized for use in critical applications including aerospace and life support applications. Use of products in these applications is fully at the risk of the Buyer. Critical applications include any system or device whose failure to perform can result in significant injury to the user.

#### LETHAL VOLTAGES

Lethal voltages could be present in the applications. Please comply with all applicable safety regulations.

#### INTELLECTUAL PROPERTY RIGHTS AND PROPRIETARY DATA

ASIC Advantage, Inc. retains all intellectual property rights in the products. Sale of products does not confer on Buyer any license to the intellectual property. ASIC Advantage, Inc. reserves the right to make changes without notice to the products at any time. Buyer agrees not to use or disclose ASIC Advantage Inc.'s proprietary information without written consent.

#### TRADEMARKS AND PATENTS

- IN-PLUG® is a registered trademark of ASIC Advantage, Inc.
- AAI's modified snubber network is patented under the US Patent # 6,233,165

## PROTECTION FOR CUSTOM SOLUTIONS

When AAI accepts to design and manufacture products to Buyer's designs or specifications, buyer has certain obligations to provide defense in a suit or proceeding claiming infringement of a patent, copyright or trademark or for misappropriation of use of any trade secrets or for unfair competition.

## **COMPLIANCE WITH LAWS**

Buyer agrees that at all times it will comply with all applicable federal, state, municipal, and local laws, orders and regulations. Buyer agrees to comply with all applicable restrictions on exports and re-exports including obtaining any required U.S. Government license, authorization, or approval. Buyer shall pay any duties, levies, taxes, brokerage fees, or customs fees imposed on the products.

## **TITLE AND DELIVERY**

All shipments of goods shall be delivered ExWorks, Sunnyvale, CA, U.S.A. Title in the goods shall not pass to Buyer until ASIC Advantage, Inc. has received in full all amounts owed by Buyer.

#### LATEST DATASHEET UPDATES

For the latest datasheet updates, visit our web page: http://www.asicadvantage.com.

## WORLDWIDE REPRESENTATIVES

To access AAI's list of worldwide representatives, visit our web page http://www.asicadvantage.com.

## **COPYRIGHTS**

Copyrights and all other proprietary rights in the Content rests with ASIC Advantage Inc. (AAI) or its licensors. All rights in the Content not expressly granted herein are reserved. Except as otherwise provided, the Content published on this document may be reproduced or distributed in unmodified form for personal non-commercial use only. Any other use of the Content, including without limitation distribution, reproduction, modification, display or transmission without the prior written consent of AAI is strictly prohibited. All copyright and other proprietary notices shall be retained on all reproductions.

#### ASIC Advantage INC.

1290-B Reamwood Ave, Sunnyvale California 94089, USA Tel: (1) 408-541-8686 Fax: (1) 408-541-8675 Website: http://www.asicadvantage.com